



Richelieu's 3W LED Invoke with Tilt & Swivel

Product # 154122170

Light Color Warm White

Kelvin Color Temperature (K) 3250 K - 3650 K

Luminous Flux 120 Lumen

DESCRIPTION

20° swivel

New high-powered 3W LED light with solid aluminum housing.

- 20° swivel with 40° lens (light beam)
- Bore hole: 1-7/8" (48 mm)
- Recess depth: 1/2" (13.5 mm)

ADVANTAGES AND BENEFITS

- High-quality Cree LED - Friction-fit installation - Average life: 50,000 hours - Recessed installation

REQUIRED PRODUCTS

Requires ONE of the following products

Sales unit



18W Power Supply
Product # 1551218

OR



Richelieu's 9W LED Power Supply
Product # 8990

OR



Complete 3-Step Plug & Play Dimmer Kit
Product # 1551170

OR



Richelieu's Complete IR On/Off Plug & Play Kit
Product # 1551090

OR



Power Supply with Integrated PIR Motion Sensor
Product # 1551018

TECHNICAL SPECIFICATIONS

Product #	154122170
Location	Inside Cabinet, Under Cabinet
Application	Kitchen
Mounting	Recessed
Luminaire	Pivoting Spots
Control System	Touch
Operation	Touch
Lighting	Accent
Finish	Brushed Nickel
Standards and Certifications	ETL
Style	Contemporary
Height	1 1/2 in
Diameter	2 1/3 in
Recessed Depth	1/2 in
Bore Hole	1 7/8 in
Lighting Type	LED
Tension (V)	12 V
Watts	3 W
Price Point	Optimum
Features	Dimmable, Touch Function

APPLICATION

Accents and perimeters, closets, furniture and bookcases, kitchen cabinets.

INCLUDED PRODUCT(S)

Includes a 59" Quick Connect cable with a plug for connections between LED lights and power supply (sold separately; see Required Products section).

IMPORTANT INFORMATION

Requires a power supply. Please see required products for options.

DISCLAIMER

Always connect the LED light to the power supply first and then connect the power supply to the mains; failure to do so may cause damage to the existing diode. There is no replacement bulb available for this light due to its life span average of 50,000 hours. Richelieu grants no warranty on LED lights if another power supply other than the one specifically prescribed for this product is used. Do not exceed the maximum wattage by connecting more lights than prescribed; damage to the power supply may result. All unused power supply output plugs must have jumper installed. Do not cut or splice wiring or the lighting system may be damaged and manufacturer's warranty is voided.

PRODUCT PHOTOS

