



LED 4 m/13' Tape Light Roll 24 V dc 58 W

Light Color

Cool White

Neutral White

Warm White

Kelvin Color Temperature (K)

3000 K

4000 K

6000 K

Luminous Flux

1320 Lumen

1440 Lumen

1560 Lumen

DESCRIPTION

Tape on a roll

Can be cut every 10 cm (3.94") or after every 6th LED.
Quick-connect options available.

ADVANTAGES AND BENEFITS

Easy-clip system to connect two strips together: no need to use any additional screws!
Available in 3 different color temperatures: - 3000° Warm White - 4000° Neutral White - 6000° Cool White Direct Quick Connect available. - Quick Connect connecting cables available in 4 lengths: choose from 2", 20", 40", and 79".

AVAILABLE PRODUCTS

| Product # | Light Color | Kelvin Color Temperature (K) | Luminous Flux |
|-----------|---------------|------------------------------|---------------|
| 50460121 | Cool White | 6000 K | 1560 Lumen |
| 50460124 | Neutral White | 4000 K | 1440 Lumen |
| 50460122 | Warm White | 3000 K | 1320 Lumen |

TECHNICAL SPECIFICATIONS

| | |
|------------------------------|---|
| Location | Inside Cabinet, Closet, Other |
| Application | Kitchen, Living Room, Commercial, Furniture, Closet |
| Mounting | Surface |
| Luminaire | Flexible Linear |
| Lighting | Accent |
| Finish | White |
| Standards and Certifications | ETL |
| Length | 13 ft |
| Width | 3/8 in |
| Lighting Type | LED |
| Tension (V) | 24 V |
| Watts | 58 W |
| Group | LED Group G |
| Price Point | Elite |
| Maximum Length | 13 ft (3.96 m) Max |
| Features | Dimmable |

APPLICATION

Accent and perimeter lighting.

INCLUDED PRODUCT(S)

Includes one power cord starter lead with each roll.

IMPORTANT INFORMATION

14.4 W per meter (3') Requires power cord if you are cutting the tape light roll to start a NEW run. 3 different lengths available with quick-connect feature: 20", 40" and 79", in black or white. Power supply required, with 3 options to choose from: - 2652412 = 2' max run - 2651236 = 6' max run - 2651260 = 13' max run

DISCLAIMER

One power cord to connect to power supply is included in each roll. If you need more power cords they are available separately. Each LED tape light roll has 3M Adhesive tape on backside. You can affix the tape into position after you have measure and mark your installation location. You only have ONE CHANCE for correct installation if you try to unpeel the tape to reposition it, it will never fully adhere again. You will require additional 3M Adhesive, sold separately. Be careful when you install the LED strip light on conducting surfaces, because the solder contact can cause a short circuit. Avoid buckling the LED strip light because the PCB board can be damaged easily. You can turn on the power supply in the final step when everything is set up.

PRODUCT PHOTOS

