



# **Lumino Tape Light - Motion Sensor Option**

**Product #** 71248030

### DESCRIPTION

A great item that can be used inside cabinets, drawers, closets, and anywhere that you need your tape lights to automatically turn on and off. Ideal for installations where there is reduced mobility. Works in dark environments.

### **ADVANTAGES AND BENEFITS**

- Max wattage on 24V is 72W max. - The perfect energy-saving closet solution! - Ideal for use in hotels.

# **TECHNICAL SPECIFICATIONS**

Product #	71248030
Lighting Type	LED
Control System	PIR
Operation	Motion Sensor
Sensor Type	Movement
Tension (V)	24 V
Style	Functional
Finish	White
Mounting	Surface
Watts	72 W
Length	1 13/16 in*
Height	29/32 in*
Width	1 3/16 in*
Price Point	Elite
Application	Closet
Material	Plastic
Features	Motion / Occupancy Sensor

#### **Disclaimer**

Measures shown with an asterisk (\*) have been converted as per your preference. These are not the official measures. To view the measures specified by the manufacturer, <u>click here</u>.

## **APPLICATION**

Use it in a toe kick with your tape lights so every time someone walks into the kitchen the toe kick lights will light up and automatically turn off when they leave - adds increased security especially for reduced mobility users.



# **INCLUDED PRODUCT(S)**

Includes a 6" female connector to directly link to power supply and a 6" male connector to connect to Richelieu's LED Lumino tape light or tape light roll.

# IMPORTANT INFORMATION

Motion Sensor Detection Range: 3 meters / 10 feet Motion Sensor Detection Degree:  $120^{\circ}$  Motion Sensor Timer: One minute after no movement is detected the lights will turn off, but as long as you are in the space and motion is being detected the lights will stay on . Size: L 2.6" x W 1.2" x D 0.8"

# **PRODUCT PHOTOS**

