



Dimmable Power Supply 12 V Hardwire

Product # DH1224

Maximum Fixtures per Driver 8

Power Supply 24 W

Output Port 6 ports

Length 8 15/32 in*

Height 2 in*

DESCRIPTION

Forward phase magnetic low voltage

- Easy installation
- 6 ft cable
- Five different watt maximums to choose from

ADVANTAGES AND BENEFITS

- Dimmable LED power supply with power cord for plug-in option or hardwire option

REQUIRED PRODUCTS

Requires the following products

Sales unit



Decora® Digital Controls with Bluetooth® Technology

Product # 109D00101

TECHNICAL SPECIFICATIONS

Product #	DH1224
Lighting Type	LED
Compatibility	Micro 12
Finish	Black
Standards and Certifications	ETL
Material	Metal
Width	2 15/32 in*
Tension (V)	12 V
Features	Dimmable

Disclaimer

Measures shown with an asterisk (*) have been converted as per your preference. These are not the official measures. To view the measures specified by the manufacturer, [click here](#).

IMPORTANT INFORMATION

- For optimal dimming, a 10% minimum load or higher on the power supply is required - Suitable for dry and damp locations - Leading edge dimming - 90 V ac to 132 V ac - 3 W minimum load * Maximum fixtures indicates the highest number of connections recommended for an average of 3 W per fixture. Please do not exceed that number. * Output ports indicates the number of connections permitted by the adapter included in the box. For more fixtures, please see 12 V Micro DC adapter in the Suggested Product section. Please do not exceed the maximum fixtures per driver. * Pictures provided for visual reference only: actual product may vary.

DISCLAIMER

* Richelieu is not responsible for damages caused by an overloaded power supply. Please follow Richelieu's recommended wattage listed in the Power Supply section of the products section. * For interior use only. * Pictures provided for visual reference only. Actual product may vary.

PRODUCT PHOTOS

